

★ **NEW!****FEATURES**

- Measurement Ranges: 30A/300A/3000A AC
- Output Sensitivity:
100mV/10mV/1mV per Amp (CENTER25)
- Output Resolution (LCD Display):
0.01A/0.1A/1A (CENTER26)
- 10" flexible sensor fit around conductors up to 3.2" in diameter.
- 18" flexible sensor fit around conductors up to 5.8" in diameter.
- TRMS Reading (CENTER 26)
- 8.5mm coil diameter allows measurement in tight spaces. (Double insulated)
- 1.8m (6 ft) cable.
- Flashing LED low battery indicator. (CENTER25)
- Dual banana plug termination for direct input into DMM. (CENTER25)
- EN 61010, CAT IV 600V , CAT III 1000V.

**ELECTRICAL SPECIFICATIONS**

Model	CENTER 25	CENTER 26
Measuring Ranges	30A/300A/3000A	30A/300A/3000A
Output Sensitivity	100mV/10mV/1mV per A (AC coupled)	0.01A/0.1A/1A
Accuracy (45/65Hz)	±1% of full scale	3% ± 5digits
Frequency Range	45-500Hz	45-500Hz
Phase Error (45/65Hz)	< ±1°	< ±1°
Position Sensitivity	±2.8% of full scale	±2.8% of full scale
Noise	0.03A/0.075A/0.5A	—
Low Battery	Indicated by a red LED	☹
Power Indicate	Indicated by a green LED	—
Power Supply	UM-4 or AAA 1.5V battery x2 (alkaline battery)	

*The specifications and other information in this catalogue are subject to change without prior notice.

CENTER[®]
CENTER TECHNOLOGY CORP.

4F, No.415, Jung-Jeng Road, Shu-Lin Dist.,
 New Taipei City 238, Taiwan
 TEL: 886-2-26763926 E-Mail : center@centertek.com
 FAX: 886-2-26763925 http ://www.centertek.com



Authorized Distributor
 APL ASIA CO., LTD.
 11/129-132 Moo.5 Lam Lukka Rd., T.Kookut, A.Lam Lukka, Pathumthani 12130 Thailand.
 TEL. 0-2995-4461-3, FAX. 0-2995-4464
 www.apl-asia.com
 EMAIL : sales@apl-asia.com
 LINE@ : @APL-ASIA