

CENTER 210/211 AC Clamp Meter/TRMS AC Clamp Meter

210 AC CLAMP METER

211 AC TRUE RMS CLAMP METER




CENTER 210 series are mid-size clamp meters. These clamps can measure up to 1000A with resolution 0.01A. 1 ms peak function is also built-in this series of clamps. This is especially useful for start current measurement. Maximum, Minimum and Hold are also standard functions for these testers.

210 is an AC clamp meter, 211 is an AC True RMS clamp meter and 212 is AC/DC True RMS meter.

FEATURES:

- True RMS(211)
- Autoranging
- Auto Power Off
- High Speed Bargraph
- Data Hold Function
- Peak Hold Function







CENTER 212 TRMS AC/DC Clamp Meter



FEATURES:

■ True RMS

1000V

- Autoranging
- Auto Power Off
- High Speed Bargraph
- Data Hold Function
- Peak Hold Function





31 LUITUATIONS			
Function	Range	Resolution	Accuracy
ACA	40A ~ 1000A	0.01A ~ 1A	±1.9%rdg+5dgts
DCA	40A ~ 1000A	0.01A ~ 1A	±2%rdg+5dgts
ACV	400V ~ 750V	0.1V ~ 1V	±1.2%rdg+5dgts
DCV	400V ~ 1000V	0.1V ~ 1V	±0.75%rdg + 2dgts
Ohms	$400\Omega\sim4000\Omega$	0.1Ω ~1Ω	±1%rdg+2dgts
Hz(A)	4KHz ~ 10KHz	1Hz	±0.1%rdg + 1dgts
Hz(V)	4KHz ~ 10KHz	1Hz	±0.1%rdg + 1dgts
-1))	Active Sound Level: ≦50Ω		
→	0-2V		

Display 3-3/4 digital display(maximum reading 3999)

Sampling Rate 2 times/sec(digital reading)

20 times/sec(analog bar indication)

 Battery
 9V battery

 Dimensions
 242x66x36 mm

 Weight
 approx.500g

Jaw Opening Diameter 35mm(210/211), 40mm(212)



Authorized Distributor APL ASIA CO., LTD. 11/129-132 Moo.5 Lamlukka Rd., Tkookut, A.Lamlukka, Pathumthani 12130 Thailand. TEL. 0-2995-4461-3, FAX. 0-2995-4464 www.apl-asia.com EMAIL : sales@apl-asia.com

LINE@: @APL-ASIA