

CENTER 200/201 AC, AC/DC Clamp Meter (Mini Size)

CENTER 200 series are our mini clamp meters. These clamps are designed with great hand held feeling and easily fit in the pocket. With the range 400A and the resolution is 0.01A that will fit most needs of an electrician. With built-in Voltage and Continuity functions, these testers are good choices for an everyday instrument in the tool box.

FEATURES:

- AC/DC Current (201)
- Pocket Size
- High Speed Bargraph
- Data Hold Function
- Touch Zero Function
- Autoranging
- Auto Power Off
- Resolution 0.01A, 0.1V
- Measuring Frequency From Current Clamp & Test Terminal



200 AC CLAMP METER

201 AC/DC CLAMP METER



CENTER 202 TRMS AC Clamp Meter (Mini Size)

CENTER 202 is for users who need True RMS AC current measurements.



FEATURES:

- True RMS
- Autoranging
- Auto Power Off
- High Speed Bargraph
- Data Hold Function



SPECIFICATIONS

| Function | Range | Resolution | Accuracy |
|----------|--------------------------|--------------|------------------|
| ACA | 40A ~ 400A | 0.01A ~ 0.1A | ±1.9%rdg + 5dgts |
| DCA | 40A ~ 400A | 0.01A ~ 0.1A | ±2.5%rdg + 5dgts |
| ACV | 400V ~ 600V | 0.1V ~ 1V | ±1.5%rdg + 5dgts |
| DCV | 400V ~ 600V | 0.1V ~ 1V | ±1%rdg + 2dgts |
| Ohms | 400Ω | 0.1Ω | ±1%rdg + 2dgts |
| Hz(A) | 20Hz ~ 10KHz | 1Hz ~ 10Hz | ±0.1%rdg + 1dgts |
| Hz(V) | 10Hz ~ 1MHz | 1Hz ~ 1KHz | ±0.1%rdg + 1dgts |
| ·)) | Active Sound Level: ≤40Ω | | |

| | |
|----------------------|---|
| Display | 3-3/4 digital(4000 count) display |
| Sampling Rate | 2 times/sec(digital reading) 20 times/sec(analog bar indication) |
| Battery | 1.5V, size AAA battery x 2 |
| Dimensions | 193x50x28 mm |
| Weight | approx.240g |
| Jaw Opening Diameter | 25mm(200/202), 30mm(201) |



Authorized Distributor
 APL ASIA CO., LTD.
 11/129-132 Moo.5 Lamlukka Rd.,T.Kookut, A.Lamlukka, Pathumthani 12130 Thailand.
 TEL. 0-2995-4461-3, FAX. 0-2995-4464
 www.apl-asia.com
 EMAIL : sales@apl-asia.com
 LINE@ : @APL-ASIA